

RS-405F/RSM-405F Series

5-port Real-time Redundant Ring Switch with 2-Fiber Port







Features >>>>

- Automatic MDI/MDI-X crossover for plug-and-play
- 3.2 Gbps high performance memory bandwidth
- Each port supports both 10/100 Mbps speed auto negotiation
- Full duplex IEEE 802.3x and half duplex backpressure flow control Built-in Cyber-Ring redundant technique
- Supports wide operating temperature from 0 °C ~ +70 °C
- Redundant Dual Power Inputs +10 V_{DC} ~ +30 V_{DC} Power failure alarm by relay output
- Modbus remote monitoring
- Supports Modbus OPC Server
- Store-and-forward architecture
- Frame buffer memory: 512 Kbit
- 1024 MAC addresses
- DIN-Rail Mounting

Introduction

The RS-405F/RSM-405F series is a 5-port Industrial Ethernet Real-time Redundant Ring Switch with 2-Fiber Port that secures data transmission by using fiber optic transmission to provide immunity from EMI/RFI interference.

Built-in ICP DAS Cyber-Ring technique enables multiple switches to be placed into a redundant ring. Typically the switch detects and recovers from a fiber or copper link failure within approximately 20 ms - for the majority of application, it is seamless. After unpacking the shipping case, it just takes one or two dip or rotary switch to make it work.

RS-405F/RSM-405F provides two power inputs that can be connected simultaneously to live DC power sources. If one of the power inputs fails, the other live source will act as a backup to automatically support the it's power needs. And the relay output facility can deliver warning signal while power or network link failure.


Specifications

4 - F		
Models	RS-405F Series	RSM-405F Series
Technology		
Standards	IEEE 802.3, 802.3u and 802.3x	
Processing Type	Store & forward, wire speed switching	
MAC Addresses	1024	
Memory Bandwidth	3.2 Gbps	
Frame Buffer Memory	512 Kbit	
Flow Control	IEEE 802.3x flow control, back pressure flow control	

Models		RS-405F Series	RSM-405F Series		
		RS-403F Selles	KSM-403F Selles		
Interface		10/100 Bara TV auto acceptation aread E/II during	war and and anti-MADI V annua diag		
RJ-45 Ports		10/100 Base-TX auto negotiation speed, F/H duplex mode, and auto MDI/MDI-X connection			
Fiber Optics Port		100 Base-FX			
LED Indicators		10/100M, Link/Act, Full duplex/Half duplex (Fiber Port)			
Ethernet Isolation	Multi mada Fibar Cablas	1500 V _{rms} 1 minute			
	Multi-mode Fiber Cables	50/125, 62.5/125 or 100/140 µm 2 km, (62.5/125 µm recommended) for full duplex			
	Distance		<u> </u>		
	Wavelength	1300 or 1310 nm			
Multi-mode	Min. TX Output	-20 dBm			
	Max. TX Output	-14 dBm			
	Max. RX Sensitivity	-32 dBm			
	Min. RX Overload	-8 dBm			
	Budget	12 dBm			
	Single-mode Fiber Cables	8.3/125, 8.7/125, 9/125 or 10/125 μm			
	Distance	30 km, (9/125 µm recommended) for full duplex			
	Wavelength	1300 nm or 1310 nm			
Single-mode	Min. TX Output	-15 dBm			
	Max. TX Output	-8 dBm			
	Max. RX Sensitivity	-34 dBm			
	Min. RX Overload	-5 dBm			
	Budget	19 dBm			
	Single-mode Fiber Cables	8.3/125, 8.7/125, 9/125 or 10/125 μm			
	Distance	60 km, (9/125 μm recommended) for full duplex			
	Wavelength	1300 nm or 1310 nm			
Single-mode (60T)	Min. TX Output	-5 dBm			
	Max. TX Output	0 dBm			
	Max. RX Sensitivity	-35 dBm			
	Min. RX Overload	-5 dBm			
	Budget	30 dBm			
Ethernet Transmission	Ethernet	2-pair UTP/STP Cat.3, 4, 5, EIA/TIA-568 100 Ω			
Distance	Fast Ethernet	2-pair UTP/STP Cat. 5, EIA/TIA-568 100 Ω			
COM1		RS-232 (TxD, RxD and GND); Non-isolated			
СОМ2		RS-485 (D2+, D2-; Self-Tuner ASIC inside); Non-isolated			
Frame Ground for El	MS Protection	Yes			
Power					
Input Voltage Range	e	+10 Vpc ~ +30 Vpc Redundant Dual Inputs (Isolat	red)		
Power Consumption	1	0.4 A @ 24 Voc			
LED Indicator		Yes			
Protection		Power reverse polarity protection			
Frame Ground for EMS Protection		Yes			
Connector		7-Pin Removable Terminal Block			
Mechanical					
Casing		Plastic	Metal		
Environmental Rating		Flammability UL 94V-0	IP30 Protection		
Dimensions (W x L x H)		64 mm x 101 mm x 118 mm	73 mm x 105 mm x 132 mm		
Installation		DIN-Rail Mounting	DIN-Rail Mounting or Wall Mounting		
Environmental					
Operating Temperature		0 °C ~ +70 °C			
Storage Temperature		-20 °C ~ +85 °C			
Ambient Relative Humidity		10% ~ 90% RH, non-condensing			
Accessories					
Included Cable		CA-090510 x 1			



Dimensions (Units: mm)



LED Functions

Standard RJ-45 female connectors are provided. A standard RJ-45 plug cable is all that is necessary to connect your device to the unit since switch that supports auto crossover.

RS/RSM-405F Series LED Indicator Functions


LED	Color	Description
Master	Red On	The switch is master of ring network
Master	Red Off	The switch is slave of ring network
	Orange On	Power input 1 is alive
PWR1	Orange Off	Power input 1 is offline
PWR2	Green On	Power input 2 is alive
	Green Off	Power input 2 is offline
	Orange On	Link to 100 Mbps
Ethernet Port	Orange Off	Link to 10 Mbps
Ethernet Port	Orange Blink	Backup Port
	Green Blink	Data Transmission
	Orange Blink	Fiber1 is active port
Fiber Port	Orange Off	Fiber1 backup port
Fiber Port	Green Blink	Fiber2 is active port
	Green Off	Fiber2 backup port

Applications

Ring Coupling

The Ring Coupling topology can connect separate Cyber-Ring network together. It is ideal for two-ring application scene.

The Ring Coupling topology not only construct individual Cyber-Ring network for each floor but also provide backup path to each other. It is a cost-effective solution to coupling ring topology.



RS-405F Series 101 64.0 88.5 37.2 36.6 118.0 110.0 Left Side View Front View

DIP/Rotary Switches

SW1: Redundancy mode configuration



	OFF	ON
1	Redundancy Mode	Tradition Mode
2	Normal State	Default Setting
3	Primary Switch	Secondary Switch
4	Ring Protocol	STP Protocol
5	Disable Ring Pair2	Enable Ring Pair2
6	Disable Ring Pair1	Enable Ring Pair1

SW2: Max. Recovery time selection



State	Time	State	Time	State	Time
F	1.5 s	9	900 ms	3	300 ms
Е	1.4 s	8	800 ms	2	200 ms
D	1.3 s	7	700 ms	1	100 ms
С	1.2 s	6	600 ms	0	N/A
В	1.1 s	5	500 ms		
Α	1.0 s	4	400 ms		

Ordering Information

RS-405FT CR	5-port Real-time Redundant Ring Switch with 2-Fiber Port, Multi-mode, ST Connector (RoHS)
RSM-405FT CR	5-port Real-time Redundant Ring Switch with 2-Fiber Port, Multi-mode, ST Connector; metal case (RoHS)
RS-405FC CR	5-port Real-time Redundant Ring Switch with 2-Fiber Port, Multi-mode, SC Connector (RoHS)
RSM-405FC CR	5-port Real-time Redundant Ring Switch with 2-Fiber Port, Multi-mode, SC Connector; metal case (RoHS)
RS-405FCS CR	5-port Real-time Redundant Ring Switch with 2-Fiber Port, Single-mode, SC Connector (RoHS)
RSM-405FCS CR	5-port Real-time Redundant Ring Switch with 2-Fiber Port, Single -mode, SC Connector; metal case (RoHS)

Accessories

CA-090510	9-Pin Female D-Sub & RJ-45 Cable, 1 M Cable
MDR-20-24	24 V/1 A, 24 W Power Supply with DIN-Rail Mounting
DIN-KA52F	24 V/1.04 A, 25 W Power Supply with DIN-Rail Mounting
DR-120-24	24 V/5 A, 120 W Power Supply with DIN-Rail Mounting